

USER MANUAL

Pro Lite

LCD Monitor

ENGLISH

DEUTSCH

FRANÇAIS

NEDERLAND

POLSKI

Pro Lite E2407HDS

Pro Lite E2407HDSV

Thank you very much for choosing the iiyama LCD monitor.

We recommend that you take a few minutes to read carefully through this brief but comprehensive manual before installing and switching on the monitor. Please keep this manual in a safe place for your future reference.





Dear user, we congratulate you on the purchase of your iiyama LCD.

All iiyama LCD monitors comply with the ISO13406-2 standard for pixel defects. For details on warranty and locally used pixel policies that apply directly after installation of your product please check the iiyama website. In case of a defect, please call your local support hotline.

Country	Phone Number	Country	Phone Number
Austria	+49 1805 44 92 62	Latvia	0 7408838
Belgium	+31 30 240 80 20	Lithuania	0 37 328442; 0 52 2101160
Bulgaria	0 2 9880300	Norway	+45 96 360 374
Czech Republik	220 121 432	Poland	0 801 449262
Denmark	0 96 360 374	Portugal	800 834 196
Estonia	0 6671796	Romania	0 21 210 38 09 33
Finland	0 9 56186130	Russia, Kaliningrad	0 4012631061
France	0 825 828 936	Slovak Republik	0 244 648 151
Germany	0 1805 44 92 62	Spain	902 014 909
Great Britain	0 870 224 95 95	Sweden	0 13 20 14 20
Greece	0 210 289 2000	The Netherlands	0 900-6664867
Hungary	06 1 814 8080; 06 1 340 9951	Ukraine	0 44 458 38 70
Italy	+49 1805 44 92 62		

Things to check before you call the iiyama information line

- | if the power cable is connected securely and turned on?
- | if the display has been turned on?
- | if the signal cable is connected securely and the correct input selected?
- | if the computer has been restarted with the display connected?
- | if the graphics card is correctly installed with the latest drivers possible?
- | if the correct native resolution has been selected via 'Display Properties'?
- | if the R/G/B signal configuration is correct?
- | if the displays On Screen Menu is shown?
- | if the correct brightness and contrast settings have been set?
- | if given display tolerances and compatibility have been considered?
- | if via the On Screen Menu you have performed a Factory Reset/Recall?

If you have checked all of the above and there is still no picture, call our information line for assistance in your country.

Before reporting the screen defect, please prepare the following information/evidence:

- | model number *
- | purchase receipt and serial number *
- | short description of the defect

Important Note:

If there is no fault found in the collected equipment after inspection, the transferring party shall incur charges for transport and administration.

* see the identification plate on the back of the case.

CE MARKING DECLARATION OF CONFORMITY

This LCD monitor complies with the requirements of the EC Directive 2004/108/EC "EMC Directive" and 2006/95/EC "Low Voltage Directive". The electro-magnetic susceptibility has been chosen at a level that gives correct operation in residential areas, business and light industrial premises and small-scale enterprises, inside as well as outside of the buildings. All places of operation are characterised by their connection to the public low voltage power supply system.



We recommend recycling of used product. Please contact your dealer or iiyama service center. Recycle information is obtained via the Internet, using the address: <http://www.iiyama.com>

You can access the Web page of different countries from there.

- We reserve the right to change specifications without notice.
- All trademarks used in this user manual are the property of their respective owners.
- As an ENERGY STAR® Partner, iiyama has determined that this product meets the ENERGY STAR® guidelines for energy efficiency.

TABLE OF CONTENTS

FOR YOUR SAFETY.....	1
SAFETY PRECAUTIONS	1
SPECIAL NOTES ON LCD MONITORS.....	3
CUSTOMER SERVICE.....	3
CLEANING.....	3
BEFORE YOU OPERATE THE MONITOR.....	4
CHECKING THE CONTENTS OF THE PACKAGE.....	4
HOW TO USE THE STAND.....	5
CONTROLS AND CONNECTORS.....	6
CONNECTING YOUR MONITOR.....	7
COMPUTER SETTING.....	8
ADJUSTING THE VIEWING ANGLE.....	8
OPERATING THE MONITOR.....	9
ADJUSTMENT MENU CONTENTS.....	10
SCREEN ADJUSTMENTS.....	14
POWER MANAGEMENT FEATURE.....	17
TROUBLE SHOOTING.....	18
APPENDIX.....	20
SPECIFICATIONS : ProLite E2407HDS-B1.....	20
SPECIFICATIONS : ProLite E2407HDS-B2.....	21
SPECIFICATIONS : ProLite E2407HDSV-B1.....	22
DIMENSIONS.....	23
COMPLIANT TIMING.....	23

FOR YOUR SAFETY

SAFETY PRECAUTIONS

WARNING

STOP OPERATING THE MONITOR WHEN YOU SENSE TROUBLE

If you notice any abnormal phenomena such as smoke, strange sounds or fumes, unplug the monitor and contact your dealer or iiyama service center immediately. Further use may be dangerous and can cause fire or electric shock.

NEVER REMOVE THE CABINET

High voltage circuits are inside the monitor. Removing the cabinet may expose you to the danger of fire or electric shock.

DO NOT PUT ANY OBJECT INTO THE MONITOR

Do not put any solid objects or liquids such as water into the monitor. In case of an accident, unplug your monitor immediately and contact your dealer or iiyama service center. Using the monitor with any object inside may cause fire, electric shock or damage.

INSTALL THE MONITOR ON A FLAT, STABLE SURFACE

The monitor may cause an injury if it falls or is dropped.

DO NOT USE THE MONITOR NEAR WATER

Do not use where water may be splashed or spilt onto the monitor as it may cause fire or electric shock.

OPERATE UNDER THE SPECIFIED POWER SUPPLY

Be sure to operate the monitor only with the specified power supply. Use of an incorrect voltage will cause malfunction and may cause fire or electric shock.

PROTECT THE CABLES

Do not pull or bend the power cable and signal cable. Do not place the monitor or any other heavy objects on the cables. If damaged, the cables may cause fire or electric shock.

ADVERSE WEATHER CONDITIONS

It is advisable not to operate the monitor during a heavy thunder storm as the continual breaks in power may cause malfunction. It is also advised not to touch the plug in these circumstances as it may cause electric shock.

CAUTION

INSTALLATION LOCATION

Do not install the monitor where sudden temperature changes may occur, or in humid, dusty or smoky areas as it may cause fire, electric shock or damage. You should also avoid areas where the sun shines directly on the monitor.

DO NOT PLACE THE MONITOR IN A HAZARDOUS POSITION

The monitor may topple and cause injury if not suitably located. Please also ensure that you do not place any heavy objects on the monitor, and that all cables are routed such that children may not pull the cables and possibly cause injury.

MAINTAIN GOOD VENTILATION

Ventilation slots are provided to keep the monitor from overheating. Covering the slots may cause fire. To allow adequate air circulation, place the monitor at least 10 cm (or 4 inches) from any walls. Do not remove the tilt stand when operating the monitor. Ventilation slots on the back of the cabinet will be blocked and the monitor may overheat if the stand is removed. This may cause fire or damage. Operating the monitor on its back, side, upside down or on a carpet or any other soft material may also cause damage.

DISCONNECT THE CABLES WHEN YOU MOVE THE MONITOR

When you move the monitor, turn off the power switch, unplug the monitor and be sure the signal cable is disconnected. If you do not disconnect them, it may cause fire or electric shock.

UNPLUG THE MONITOR

If the monitor is not in use for a long period of time it is recommended that it is left unplugged to avoid accidents.

HOLD THE PLUG WHEN DISCONNECTING

To disconnect the power cable or signal cable, always pull it by the plug. Never pull on the cable itself as this may cause fire or electric shock.

DO NOT TOUCH THE PLUG WITH WET HANDS

Pulling or inserting the plug with wet hands may cause electric shock.

WHEN YOU INSTALL THE MONITOR ON YOUR COMPUTER

Be sure the computer is strong enough to hold the weight of the monitor, otherwise, you may damage your computer.

DO NOT PUT FLOPPY DISKS NEAR THE SPEAKERS

Magnetically recorded data, such as on a floppy disk, may become corrupted by the magnetic field produced by the speakers if the disks are placed on or near the speakers.

OTHERS

ERGONOMIC RECOMMENDATIONS

To eliminate eye fatigue, do not operate the monitor against a bright background or in a dark room. For optimal viewing comfort, the monitor should be just below eye level and 40-60 cm (16-24 inches) away from your eyes. When using the monitor over a prolonged time, a ten minute break every hour is recommended as looking at the screen continuously can cause eye strain.

SPECIAL NOTES ON LCD MONITORS

The following symptoms are normal with LCD monitors and do not indicate a problem.

NOTE

- When you first turn on the LCD monitor, the picture may not fit in the display area because of the type of computer that is used. In this case, adjust the picture position to the correct position.
- Due to the nature of the backlight, the screen may flicker during initial use. Turn off the Power Switch and then turn it on again to make sure the flicker disappears.
- You may find slightly uneven brightness on the screen depending on the desktop pattern you use.
- Due to the nature of the LCD screen, an afterimage of the previous screen may remain after switching the image, when the same image is displayed for hours. In this case, the screen is recovered slowly by changing the image or turning off the Power Switch for hours.
- Contact your dealer or iiyama service center for the backlight replacement when the screen is dark, flickering or not lighting up. Never attempt to replace it by yourself.

CUSTOMER SERVICE

NOTE

- The fluorescent light used in the LCD monitor may have to be periodically replaced. For the warranty coverage on this component, please check with local iiyama service center.
- If you have to return your unit for service and the original packaging has been discarded, please contact your dealer or iiyama service center for advice or replacement packaging.

CLEANING

WARNING

- If you drop any materials or liquids such as water into the monitor when cleaning, unplug the power cable immediately and contact your dealer or iiyama service center.

CAUTION

- For safety reasons, turn off the power switch and unplug the monitor before you clean it.

NOTE

- To protect the LCD panel, do not scratch or rub the screen with a hard object.
- Never use any of the following strong solvents. These will damage the cabinet and the LCD screen.

Thinner	Spray-type cleaner
Benzine	Wax
Abrasive cleaner	Acid or Alkaline solvent
- Touching the cabinet with any product made from rubber or plastic for a long time may cause degeneration or loss of paint on the cabinet.

CABINET

Stains can be removed with a cloth lightly moistened with a mild detergent solvent. Then wipe the cabinet with a soft dry cloth.

LCD

Periodic cleaning with a soft dry cloth is recommended.

SCREEN

Don't use tissue paper etc. because these will damage the LCD screen.

BEFORE YOU OPERATE THE MONITOR

FEATURES

- ◆ 60cm (24") TFT Color LCD Monitor
- ◆ Supports Resolutions up to 1920 × 1080
- ◆ High Contrast 1000:1 , ACR Function Available/ High Brightness 300cd/m² / Quick Response Time 2ms (Gray to Gray)
- ◆ Stereo Speakers
2 × 3W Stereo Speakers
- ◆ HDMI interface:ProLite E2407HDS-B1
- ◆ Plug & Play VESA DDC1/2B Compliant
Windows® 95/98/2000/Me/XP/Vista Compliant
- ◆ Power Management (ENERGY STAR® VESA DPMS Compliant)
- ◆ VESA Mounting Standard (100mm x 100mm) Compliant

CHECKING THE CONTENTS OF THE PACKAGE

The following accessories are included in your package. Check to see if they are enclosed with the monitor. If anything is missing or damaged, please contact your local iiyama dealer or regional iiyama office.

- | | | |
|-----------------|---------------|---------------|
| ■ Power Cable*1 | ■ VGA Cable | ■ Audio Cable |
| ■ DVI-D Cable*2 | ■ User Manual | ■ Stand |

CAUTION *1 The rating of the Power Cable enclosed in 120V area is 10A/125V. If you are using a power supply higher than this rating, then a power cable with a rating of 10A/250V must be used. However, all guarantees and warranties are void for any problems or damage caused by a power cable not supplied by iiyama.

*2 Not available for ProLite E2407HDSV

HOW TO USE THE STAND

The monitor is shipped with the stand detached. Be sure to attach the stand before operating the display and remove it if it is necessary to re-box.


CAUTION

- Install the Stand on a stable surface. The monitor may cause injury or damage if it falls or is dropped.
- Do not give a strong impact to the monitor. It may cause damage.
- Unplug the monitor before installation to avoid electric shock or damage.

1. Lay the monitor flat on a table with front face down (see Fig 1). Put a piece of soft cloth on the table beforehand to prevent the monitor from being scratched.
2. Unpack the stand and mount it onto the monitor base with aligning it to the hook (see Fig 2).
3. Slide the stand upward until it makes a click sound, indicating it is fixed (see Fig 3).
4. Stand the monitor up (see Fig 4).



(Fig 1)



(Fig 2)




(Fig 3)



(Fig 4)

CONTROLS AND CONNECTORS



- ① Menu / Input Select shortcut keys ([1]) *1
- ② Scroll Down / Brightness/Contrast/ACR/ECO Mode shortcut keys (▼)
- ③ Scroll Up / OptiColor Mode (▲) *4
- ④ Select / Input select ([2])
- ⑤ Power Indicator

NOTE Blue: Normal operation
Orange: Power Management

The monitor enters into power management mode which reduces the power consumption to less than 1W when receiving no horizontal and/or vertical sync signal.

- ⑥ Power Switch (⏻)
- ⑦ AC Connector (Power IN)
- ⑧ DVI-D 24Pin Connector (DVI)
- ⑨ HDMI Connector (HDMI) *2
- ⑩ D-SUB mini 15pin Connector (VGA)
- ⑪ Audio Connector (AUDIO IN)
- ⑫ Keyhole for Security Lock *3
- ⑬ Speakers

NOTE *1 Input Select shortcut keys is available under no signal input.

*2 Available for ProLite E2407HDS-B1 only.

*3 You can fasten a security lock and cable to prevent the monitor from being removed without your permission.



*4 OptiColor Mode: Press the ▲ Button when the Menu is not displayed.

CONNECTING YOUR MONITOR

- ① Ensure that both the computer and the monitor are switched off.
- ② Connect the computer to the monitor with the signal cable.
- ③ Connect the monitor to the audio equipment with the Audio Cable for computer when using the audio features.
- ④ Connect the Power Cable to the monitor first and then to the power supply.

- NOTE**
- The signal cables used for connecting the computer and monitor may vary with the type of computer used. An incorrect connection may cause serious damage to both the monitor and the computer. The cable supplied with the monitor is for a standard 15 pin D-Sub connector. If a special cable is required please contact your local iiyama dealer or regional iiyama office.
 - For connection to Macintosh computers, contact your local iiyama dealer or regional iiyama office for a suitable adaptor.
 - Make sure you tighten the finger screws at each end of the signal cable.

[Example of Connection]



NOTE

- ① Power Cable (Accessory)
- ② DVI-D Cable (Accessory)
- ③ HDMI Cable (not Supplied)
- ④ D-Sub Signal Cable (Accessory)
- ⑤ Audio Cable (Accessory)

COMPUTER SETTING

■ Signal Timing

Change to the desired signal timing listed on page 23: COMPLIANT TIMING.

■ Windows 95/98/2000/Me/XP/Vista Plug & Play

The iiyama LCD monitor complies with DDC1/2B of VESA standard. The Plug & Play function runs on Windows 95/98/2000/Me/XP/Vista by connecting the monitor to DDC1/2B compliant computer with the Signal Cable supplied.

For installation on Windows 95/98/2000/Me/XP/Vista: The monitor Information File for iiyama monitors may be necessary for your computer and obtained via the Internet, using the address:



<http://www.iiyama.com>

NOTE

- For additional information on how to download the driver for your touch screen monitor, please access the internet site noted above.
- Monitor Drivers are not required in most cases for Windows Vista, Macintosh or Unix operating systems. For further information, please contact your computer dealer first for advice.

ADJUSTING THE VIEWING ANGLE

- For optimal viewing it is recommended to look at the full face of the monitor.
- Hold the stand so that the monitor does not topple when you change the monitor's angle.
- You are able to adjust the monitor's angle up to 20 degrees backward. (The indication of 20 degrees: tilted LCD panel holds for a moment at this point. Tilt the panel gently; using too much force can easily cause the tilt angle to exceed 20 degrees.)
- In order to ensure a healthy and relaxed body position when using the monitor at visual display workstations, it is recommended that the adjusted tilt angle should not exceed 10 degrees. Adjust the monitor's angle to your own preference.




NOTE

- Do not touch the LCD screen when you change the angle. It may cause damage or break the LCD screen.
- Careful attention is required not to catch your fingers or hands when you change the angle.
- Do not tilt the post beyond 20 degrees except when repacking the monitor in its box. To do so may cause the monitor to fall over and break.


OPERATING THE MONITOR


To create the best picture, your iiyama LCD monitor has been preset at the factory with the COMPLIANT TIMING shown on page 23. You are also able to adjust the picture by following the button operation shown below. For more detailed adjustments, see page 14 for SCREEN ADJUSTMENTS.

- ① **Press the Menu Button to start the On Screen Display feature. There are additional Menu items which can be switched by using the ▲/▼ Buttons.**




- ② **Select the Menu item which contains the adjustment icon relating to the adjustment you want to make. Press the Select Button. Then, use the ▲/▼ Buttons to highlight the desired adjustment icon.**
- ③ **Press the Select Button again. Use the ▲/▼ Buttons to make the appropriate adjustment or setting.**

For example, to correct for vertical position, select Menu item of Manual Image Adjust and then press the Select Button. Then, select  (H. / V.Position) by using the ▲/▼ Buttons.




An adjustment page appears after you press the Select Button. Press the Select Button again. Then, use the ▲/▼ Buttons to change the vertical position settings. The vertical position of the overall display should be changing accordingly while you are doing this.












NOTE

- When button operations are aborted during adjustment, On-Screen Display disappears when the time set for the OSD Time Out has passed. Also, press the Menu button to quickly turn off the On-Screen Display.
- Any changes are automatically saved in the memory when the On Screen Display disappears. Turning off the power should be avoided while using the Menu.
- Adjustments for H. / V. Position, H.Size and Fine Tune are saved for each signal timing. Except for these adjustments, all other adjustments have only one setting which applies to all signal timings.

ADJUSTMENT MENU CONTENTS

Auto Image Adjust  Auto Image Adjust		
Adjustment Item	Problem / Option	Button to Press
Auto Image Adjust * Only Analog input	Adjust H. / V. Position, H.Size and Fine Tune automatically.	
NOTE The screen becomes dark for approximately five seconds during the adjustment.		

* For best results, use the Auto Adjust in conjunction with the adjustment pattern. See page 14 for SCREEN ADJUSTMENTS.

Contrast/Brightness  Contrast/Brightness		
Adjustment Item	Problem / Option	Button to Press
Contrast*3 Direct	Too dull Too intense	   
Brightness *1,3 Direct	Too dark Too bright	   
ACR*2 Direct	On	Increased contrast ratio
	Off	typical contrast ratio
ECO Mode Direct	On	Brightness of back light is reduced.
	Off	Normal

*1 Adjust the Brightness when you are using the monitor in a dark room and feel the screen is too bright. Can not select when ACR is On.

*2 ACR can not enable the same time when ECO Mode is on.

*3 Contrast and Brightness adjustment disabled when ECO Mode is active or when Opticolor Mode is set to Text or Cinema or Game or Scenery.

NOTE

Contrast, Brightness, ACR and ECO Mode are switched as follows by pressing the ▲/▼ Button successively.

⇒ Contrast → Brightness → ACR → ECO Mode ⇐


Direct

You can skip the Menu items and display an adjustment scale directly by using the following button operations.

- Contrast/Brightness/ ACR/ ECO Mode : Press the ▼ Button when the Menu is not displayed.







Input Select*1 Input Select

Adjustment Item	Problem / Option	Button to Press
Input Select	VGA	Select the VGA input
	DVI	Select the DVI input
	HDMI*2	Select the HDMI input
	AUTO	Select the AUTO input

Direct ■ You can display the Input Select Menu by pressing the  button under no signal input.

*1 Not available for ProLite E2407HDSV
 *2 Available for ProLite E2407HDS-B1 only.







Audio Adjust Audio Adjust

Adjustment Item	Problem / Option	Button to Press
Volume	Too soft	 
	Too loud	 
Mute	 Return the sound volume to the previous level.	
	 Turn off the sound temporarily.	

NOTE ■ Mute off and on are switched as follows by pressing the Select Button successively.

> Mute off → Mute on <

Color Adjust Color Adjust

Adjustment Item	Problem / Option	Button to Press
9300K	Bluish white	
6500K	Reddish white	
5400K	Greenish white	
User Color	 	Too weak   Too strong  
	Red	
	Green	
	Blue	

Information Information

Information VGA

H. Frequency: 67.5 KHz


V. Frequency: 60.0 Hz

Resolution: 1920x 1080

Pixel Clock: 148.5 MHz

Serial Number: 1103291100001

































Model Number: PLE2407HDS

 Exit

Displays information regarding the current input signal coming from the graphic card in your computer.

NOTE

See your graphic card user guide for more information about changing the resolution and refresh

Manual Image Adjust		Manual Image Adjust	
Adjustment Item		Problem / Option	Button to Press
 Horizontal Size*1		 Too narrow  Too wide	   
 H./V. Position*1	H. Position	 Too far to the left  Too far to the right	   
	V. Position	 Too low  Too high	   
 Fine Tune*1		To correct flickering text or lines	   
 Sharpness		Adjust the picture quality at resolutions of less 1920 x 1080. You can change the picture quality (3 steps).	   
 Video Mode Adjust	Full Screen	Select full screen	
	Over Screen	Select over screen	
	Aspect Ratio*2	Select Aspect ratio	
 OptiColor Mode	Standard	For general windows environment and monitor default setting	
	Game	For PC game environment	
	Cinema	For movie and video environment	
	Scenery	For displaying outdoor scenery images	
	Text	For text editing and viewing in a word processing environment	

NOTE H. Position and V. Position are switched as follows by pressing the▲/▼Button successively.















➔ H. Position ➔ V. Position

*1 Only Analog input.

*2 It can display in the center of the screen with a 4:3, 5:4 or 16:10 aspect ratio when input video resolution is 4:3, 5:4 or 16:10 .

Standard, Game,Cinema, Scenery and Text are switched as follows by pressing the ▲/▼ Button successively.

➔ Standard ➔ Game ➔ Cinema ➔ Scenery ➔ Text

Setup Menu		Setup Menu		
Adjustment Item	Problem / Option		Button to Press	
 Language Select	English	English	Suomi	Finnish
	Français	French	日本語	Japanese
	Deutsch	German	中文简体	Simplified Chinese
	Espanol	Spanish	中文繁体	Traditional Chinese
	Italiano	Italian		
 OSD Position	H.Position	OSD is too far to the left		 
		OSD is too far to the right		 
	V.Position	OSD is too low		 
		OSD is too high		 
 OSD Time Out	You can set the OSD display duration time between 5 and 60 seconds.			 
 OSD Background	on	Return the background of OSD		
	off	The background of OSD is made transparent		

Memory Recall		Memory Recall	
Adjustment Item	Problem / Option		Button to Press
Memory Recall	Factory-preset data is restored.		

SCREEN ADJUSTMENTS

Adjust the image by following the procedure below to get the desired picture when selecting Analog input.

- The screen adjustments described in this manual are designed to set image position and minimize flicker or blur for the particular computer in use.
- The monitor is designed to provide the best performance at resolution of 1920 × 1080, but can not provide the best at resolutions of less than 1920 × 1080 because the picture is automatically stretched to fit the full screen. It is recommended to operate at resolution of 1920 × 1080 in normal use.
- Displayed text or lines will be blurred or irregular in thickness when the picture is stretched due to the screen enlargement process.
- It is preferable to adjust the image position and frequency with the monitor controls, rather than the computer software or utilities.
- Perform adjustments after a warm-up period of at least thirty minutes.
- Additional adjustments may be required after the Auto Adjust depending on the resolution or signal timing.
- The Auto Adjust may not work correctly when displaying the picture other than the screen adjustment pattern. In this case, manual adjustments are required.

There are two ways to adjust the screen. One way is automatic adjustment for Position, H.Size and Fine Tune. The other way is performing each adjustment manually.

Perform the Auto Adjust first when the monitor is connected to a new computer, or resolution is changed. If the screen has a flicker or blur, or the picture does not fit in the display area after performing the Auto Adjust, manual adjustments are required. Both adjustments should be made by using the screen adjustment pattern (Test.bmp) obtained via the IYAMA web site (<http://www.iiyama.com>).


Adjust the image by following the procedure below to get the desired picture.

This manual explains adjustment under Windows 95/98/2000/Me/XP/Vista.


- ① **Display the picture at the optimum resolution.**
- ② **Enter the Test.bmp (screen adjustment pattern) to wallpaper.**

- NOTE**
- Consult the appropriate documentation for doing this.
 - Test.bmp is made at resolution of 1280 × 1024 Set the display position to center in the wallpaper setting dialogue box. If you use Microsoft® PLUS! 95/98 cancel the setting of "Stretch desktop wallpaper to fit the screen".


[Adjustment pattern]




- ③ Press the Auto Button. (Auto Adjust)
- ④ Adjust the image manually by following procedure below when the screen has a flicker or blur, or the picture does not fit in the display area after performing the Auto Adjust.
- ⑤ Adjust the V.Position so that the top and bottom of the picture frame will fit to the display area.



- ⑥ 1) Adjust the H.Position so that the left side of the picture frame will move to the left edge of the display area.




- 2) Stretch the right side of the picture frame to the right edge of the display area by adjusting the H.Size.



- NOTE**
- When the left side of the picture frame moves apart from the left edge of the display area during the H.Size adjustment, adjust steps 1) and 2).
 - Another way to make the H.Size adjustment is to correct the vertical wavy lines in the zebra pattern.
 - The picture may flicker during the H.Size, H.Position and V.Position adjustment.
 - In case the picture frame is bigger or smaller than the data display area after the H.Size adjustment, repeat steps from ③.

- ⑦ **Adjust the Fine Tune to correct horizontal wavy noise, flicker or blur in the zebra pattern.**

**NOTE**

- In case the strong flicker or blurs remain on a part of the screen, repeat steps ⑥ and ⑦ because the H.Size may not be adjusted correctly. If the flicker or blurs still remain, set the refresh rate of computer to low (60Hz) and repeat steps from ③ again.
 - Adjust the H.Position after the Fine Tune adjustment if the horizontal position moves during the adjustment.
- ⑧ **Adjust the Brightness and Color Adjust to get the desired picture after you complete the H.Size and Fine Tune adjustments.**
Put back your favorite wallpaper.


POWER MANAGEMENT FEATURE

The power management feature of this product complies with power saving requirement of ENERGY STAR® and VESA DPMS. When activated, it automatically reduces unnecessary power consumption of the monitor when your computer is not in use.

To use the feature, the monitor needs to be connected to a VESA DPMS compliant computer. There is a power management step the monitor takes as described below. The power management function, including any timer settings is configured by the operating system. Check your operating system manual for information on how this can be configured.

■ Power Management Mode

When the H-sync signal / V-sync signal / H and V sync signals from the computer are off, the monitor enters into Power Management Mode which reduces the power consumption to less than 1W. The screen becomes dark, and the power indicator turns to orange. From Power Management Mode, the image reappears in several seconds when either the keyboard or the mouse are touched again.



NOTE

- Even when using the power management mode, the monitor consumes electricity. Turn off the Power Switch whenever the monitor is not in use, during the night and weekends, to avoid unnecessary power consumption.
- It is possible that the video signal from the computer may be on while the H or V sync signal is missing. In this instance, the POWER MANAGEMENT feature may not work properly.

TROUBLE SHOOTING

If the monitor fails to operate correctly, please follow the steps below for a possible solution.

1. Perform the adjustments described in OPERATING THE MONITOR, depending on the problem you have. If the monitor does not get a picture, skip to 2.
2. Consult the following items if you cannot find an appropriate adjustment item in OPERATING THE MONITOR or if the problem persists.
3. If you are experiencing a problem which is not described below or you cannot correct the problem, discontinue using the monitor and contact your dealer or iiyama service center for further assistance.

Problem	Check
① The picture does not appear. (Power indicator does not light up.) (Power indicator is blue.) (Power indicator is orange.)	<input type="checkbox"/> The Power Cable is firmly seated in the socket. <input type="checkbox"/> The Power Switch is turned ON. <input type="checkbox"/> The AC socket is live. Please check with another piece of equipment. <input type="checkbox"/> If the blank screen saver is in active mode, touch the keyboard or the mouse. <input type="checkbox"/> Increase the Contrast and/or Brightness. <input type="checkbox"/> The computer is ON. <input type="checkbox"/> The Signal Cable is properly connected. <input type="checkbox"/> The signal timing of the computer is within the specification of the monitor. <input type="checkbox"/> If the monitor is in power management mode, touch the keyboard or the mouse. <input type="checkbox"/> The computer is ON. <input type="checkbox"/> The Signal Cable is properly connected. <input type="checkbox"/> The signal timing of the computer is within the specification of the monitor.
② The screen is not synchronized.	<input type="checkbox"/> The Signal Cable is properly connected. <input type="checkbox"/> The signal timing of the computer is within the specification of the monitor. <input type="checkbox"/> The video output level of the computer is within the specification of the monitor.
③ The screen position is not in the center.	<input type="checkbox"/> The signal timing of the computer is within the specification of the monitor.
④ The screen is too bright or too dark.	<input type="checkbox"/> The video output level of the computer is within the specification of the monitor.
⑤ The screen is shaking.	<input type="checkbox"/> The power voltage is within the specification of the monitor. <input type="checkbox"/> The signal timing of the computer is within the specification of the monitor.

Problem

Check

- | | |
|---------------------------------------|--|
| ⑥ No sound. | <input type="checkbox"/> The audio equipment (computer etc.) is ON. |
| | <input type="checkbox"/> The Audio Cable is properly connected. |
| | <input type="checkbox"/> The Volume is turned up. |
| | <input type="checkbox"/> The Mute is OFF. |
| | <input type="checkbox"/> The audio output level of the audio equipment is within the specification of the monitor. |
| ⑦ The sound is too loud or too quiet. | <input type="checkbox"/> The audio output level of the audio equipment is within the specification of the monitor. |
| ⑧ A strange noise is heard. | <input type="checkbox"/> The Audio Cable is properly connected. |

RECYCLING INFORMATION

For better environment protection please don't dispose your monitor.

Please visit our web site: www.iiyama.com/recycle for monitor recycling.

APPENDIX

SPECIFICATIONS: ProLite E2407HDS-B1

ENGLISH

LCD Panel	Size/ Category	Diagonal: 60cm / 24.0"
	Pixel pitch	0.2715 mm H × 0.2715mm V
	Brightness	300cd/m ² (Typical)
	Contrast ratio	1000 : 1 (Typical), ACR function available
	Viewable angle	Right / Left : 85 degrees each, Up:80 degrees, Down: 80 degrees (Typical)
	Response time	2ms (OD, Gray to Gray)
Display Colors	Approx. 16.7M	
Sync Frequency	Horizontal: 31.0-80.0kHz, Vertical: 56-75Hz	
Maximum Resolution	1920 × 1080	
Input Connector	D-Sub mini 15 pin,DVI-24 pin,HDMI	
Plug & Play	VESA DDC1/2B™	
Input Sync Signal	Separate sync: TTL, Positive or Negative	
Input Video Signal	Analog: 0.7Vp-p (Standard), 75Ω, Positive Digital (DVI): Digital Visual Interface standard Rev. 1.0 compliance Digital (HDMI): HDMI (1.3)	
Input Audio Connector	ø 3.5mm mini jack (Stereo)	
Input Audio Signal	1Vrms maximum	
Speakers	3W × 2 (Stereo speakers)	
Maximum Screen Size	521.3mm W × 293.2mm H / 20.51" W × 11.54" H	
Power Source	100-240VAC, 50/60Hz, 1.8A	
Power Consumption	46W (Typ), Power management mode: 1W maximum*	
Dimensions / Net Weight	560.0 × 404.5 × 220.0 mm / 22.0 × 15.9 × 8.6 (W×H×D), 5.0kg / 11.0lbs	
Tilt Angle	20 degrees (Up: 0-20 degrees)	
Environmental Considerations	Operating: Temperature 5 to 35°C / 41 to 95°F Humidity 10 to 80% (No condensation) Storage: Temperature -20 to 60°C / -4 to 140°F Humidity 10 to 70% (No condensation)	
Approvals	CE,TUV/Baurt,Energy star	

NOTE * Condition: Audio equipment is not connected.

APPENDIX

SPECIFICATIONS: ProLite E2407HDS-B2

LCD Panel	Size/ Category	Diagonal: 60cm / 24.0"
	Pixel pitch	0.2715 mm H × 0.2715mm V
	Brightness	300cd/m ² (Typical)
	Contrast ratio	1000 : 1 (Typical), ACR function available
	Viewable angle	Right / Left : 85 degrees each, Up:80 degrees, Down: 80 degrees (Typical)
	Response time	2ms (OD, Gray to Gray)
Display Colors	Approx. 16.7M	
Sync Frequency	Horizontal: 31.0-80.0kHz, Vertical: 56-75Hz	
Maximum Resolution	1920 × 1080	
Input Connector	D-Sub mini 15 pin,DVI-24 pin	
Plug & Play	VESA DDC1/2B™	
Input Sync Signal	Separate sync: TTL, Positive or Negative	
Input Video Signal	Analog: 0.7Vp-p (Standard), 75Ω, Positive Digital (DVI): Digital Visual Interface standard Rev. 1.0 compliance	
Input Audio Connector	ø 3.5mm mini jack (Stereo)	
Input Audio Signal	1Vrms maximum	
Speakers	3W × 2 (Stereo speakers)	
Maximum Screen Size	521.3mm W × 293.2mm H / 20.51" W × 11.54" H	
Power Source	100-240VAC, 50/60Hz, 1.8A	
Power Consumption	46W (Typ), Power management mode: 1W maximum*	
Dimensions / Net Weight	560.0 × 404.5 × 220.0 mm / 22.0 × 15.9 × 8.6 (W×H×D), 5.0kg / 11.0lbs	
Tilt Angle	20 degrees (Up: 0-20 degrees)	
Environmental Considerations	Operating: Temperature 5 to 35°C / 41 to 95°F Humidity 10 to 80% (No condensation) Storage: Temperature -20 to 60°C / -4 to 140°F Humidity 10 to 70% (No condensation)	
Approvals	CE,TUV/Baurt,Energy star	

NOTE * Condition: Audio equipment is not connected.

APPENDIX


SPECIFICATIONS: ProLite E2407HDSV-B1

ENGLISH

LCD Panel	Size/ Category	Diagonal: 60cm / 24.0"
	Pixel pitch	0.2715 mm H × 0.2715mm V
	Brightness	300cd/m ² (Typical)
	Contrast ratio	1000 : 1 (Typical), ACR function available
	Viewable angle	Right / Left : 85 degrees each, Up:80 degrees, Down: 80 degrees (Typical)
	Response time	2ms (OD, Gray to Gray)
Display Colors	Approx. 16.7M	
Sync Frequency	Horizontal: 31.0-80.0kHz, Vertical: 56-75Hz	
Maximum Resolution	1920 × 1080	
Input Connector	D-Sub mini 15 pin	
Plug & Play	VESA DDC1/2B™	
Input Sync Signal	Separate sync: TTL, Positive or Negative	
Input Video Signal	Analog: 0.7Vp-p (Standard), 75Ω, Positive	
Input Audio Connector	ø 3.5mm mini jack (Stereo)	
Input Audio Signal	1Vrms maximum	
Speakers	3W × 2 (Stereo speakers)	
Maximum Screen Size	521.3mm W × 293.2mm H / 20.51" W × 11.54" H	
Power Source	100-240VAC, 50/60Hz, 1.8A	
Power Consumption	46W (Typ), Power management mode: 1W maximum*	
Dimensions / Net Weight	560.0 × 404.5 × 220.0 mm / 22.0 × 15.9 × 8.6 (W×H×D), 5.0kg / 11.0lbs	
Tilt Angle	20 degrees (Up: 0-20 degrees)	
Environmental Considerations	Operating: Temperature 5 to 35°C / 41 to 95°F Humidity 10 to 80% (No condensation) Storage: Temperature -20 to 60°C / -4 to 140°F Humidity 10 to 70% (No condensation)	
Approvals	CE, TUV/Baurt, Energy star	

NOTE * Condition: Audio equipment is not connected.

DIMENSIONS



COMPLIANT TIMING

PC Input

Video Mode		Horizontal Frequency	Vertical Frequency	Dot Clock
VESA	VGA 640 × 480	31.469kHz	59.940Hz	25.175MHz
		37.500kHz	75.000Hz	31.500MHz
	SVGA 800 × 600	37.879kHz	60.317Hz	40.000MHz
		48.077kHz	72.188Hz	50.000MHz
		46.875kHz	75.000Hz	49.500MHz
	XGA 1024 × 768	48.363kHz	60.004Hz	65.000MHz
		56.476kHz	70.069Hz	75.000MHz
		60.023kHz	75.029Hz	78.750MHz
	SXGA 1280 × 1024	63.981kHz	60.020Hz	108.000MHz
		79.976kHz	75.025Hz	135.000MHz
WXGA+ 1440 × 900	55.935kHz	59.887Hz	106.500MHz	
	70.635kHz	74.984Hz	136.750MHz	
UXGA 1600 × 1200	75.000kHz	60.000Hz	162.000MHz	
WSXGA+ 1680 × 1050	65.290kHz	60.000Hz	146.250MHz	
Full HD 1920 × 1080	67.500kHz	60.000Hz	148.500MHz	
VGA TEXT	720 × 400	31.469kHz	70.087Hz	28.322MHz*

NOTE

* DVI, HDMI Input is not compliant.

Video input 480P/720P/1080i/1080P