ONKYO



LS-T10

TV Speaker System

Thank you for purchasing an Onkyo product. Please read this manual thoroughly before making connections and plugging in your new Onkyo product.

Following the instructions in this manual will enable you to obtain optimum performance and listening enjoyment from your new product.

Please retain this manual for future reference.

## Trademarks and Licensing



Manufactured under license from Dolby Laboratories. Dolby and the double-D symbol are trademarks of Dolby



The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Onkyo is under license. Other trademarks and trade names are those of their respective owners.



AuraSphere™ is a trademark of Onkyo Corporation.


AuraSphere is a listening experience technology developed by Onkyo Corporation and Sonic Emotion ag.

# D1308-0

# PACKAGE CONTENTS

Make sure you have the following items before use.

- The number in parenthesis indicates the quantity.
- **Placement**  In catalogs and on packaging, the letter at the end of the product name indicates the color.





AC adapter (1)










A lithium-ion battery (CR2025) is supplied in the remote control at the time of purchase










# **PREPARATION**

Select an appropriate placement for your environment.

- To enjoy the best sound, do not place an object on both sides of the unit. Furthermore, mount this unit carefully since the subwoofer unit is housed on its bottom face.
- Mount this unit on a firm surface such as a low board.

## **Mounting under TV**



## Accessories to be prepared: Cushion


To prevent vibration, mount this unit after attaching the supplied cushions to the feet of the TV stand. Using the supplied cushions will allow you to limit the effect of vibrations on the TV.

## 1. Attach the supplied cushions to the feet of the TV stand.

- Be very careful when attaching the cushions. Depending on the size and  $(\rightarrow$  See 7 to 8 pages) weight of the TV in particular, be sure to have at least two people do the job to 4. Mount the TV on the center of the top face of this unit.
- Mount the unit correctly by referring to the figure below. Wrap the TV with a blanket or soft cloth to not scratch it and work carefully

3. Connect all cables to the unit.


When the supplied cushions and the feet of the TV do not match, cut and



- Place the TV stand in such a way that its center matches that of this unit.
  - Shaded area: Mountable range


## Precautions for mounting this unit under TV • TVs that can be placed on top of this unit are those having a mass of 77 lbs (35 kg)

- or less, stand width of 26 1/2" (674 mm) or less, and depth of 10 3/8" (265 mm) or
- By referring to the figure on the left, mount the TV on the center of the mountable



- For TV tip-over/fall prevention measures, see the TV owner's manual.
- Onkyo is not responsible for accidents or damage caused by improper installation,

- range. If the TV protrudes from any of the mountable range, the TV may tip over and



Connections

- Connect the TV and this unit using one of the possible connection cables.




- improper cushion attachment, improper use or natural calamity, etc.

USB port

Connect a USB flash drive.

Turn on the TV.

- For details on operation, see the "BASIC OPERATION" (→ P.11).
  - The unit can be operated with your existing TV remote controller. For details on operation, see the "Using TV Remote Controller" ( $\rightarrow$  P.17).



- Liegnitzerstrasse 6, 82194 Groebenzell, GERMANY Tel: +49-8142-4401-0 Fax: +49-8142-4208-213 (On the buttons of the unit, switches http://www.eu.onkvo.com/ Onkyo Europe Electronics GmbH (UK Branch) in the order of  $\square$  TV  $\rightarrow \blacktriangleleft$  USB  $\rightarrow$ 
  - Meridien House, Ground floor, 69 71 Clarendon Road, Watford, Hertfordshire, WD17 1DS, United Kingdom

18 Park Way, Upper Saddle River, N.J. 07458, U.S.A.

For Dealer, Service, Order and all other Business Inquiries

Tel: +44 (0)8712-00-19-96 Fax: +44 (0)8712-00-19-95

Kitahama Chuo Bldg, 2-2-22 Kitahama, Chuo-ku, OSAKA 541-0041, JAPAN

ONKYO

Onkyo Corporation

http://www.onkyo.com/

The Americas
Onkyo U.S.A. Corporation

http://www.us.onkvo.com/

http://www.us.onkyo.com/

1-800-229-1687

For Product Support Team Only

Tel: 201-785-2600 Fax: 201-785-2650

Onkyo Europe Electronics GmbH

Unit 1033, 10/F, Star House, No 3, Salisbury Road, Tsim Sha Tsui Kowloon, Hong Kong, Tel: 852-2429-3118 Fax: 852-2428-9039

Onkyo Ching PRC (Mainland)

Tel: 86-21-52131366 Fax: 86-21-52130396

Asia, Oceania, Middle East, Africa

## Please contact an Onkyo distributor referring to Onkyo SUPPORT site.

http://www.intl.onkvo.com/support/

The above-mentioned information is subject to change without prior notice.

Visit the Onkyo web site for the latest update.

(C) Copyright 2013 Onkyo Corporation Japan. All rights reserved



shape the cushions for use as needed.

ANALOG

Connect the supplied stereo mini

plug cable to input audio.

COAXIAL iack

input the sound.

Connect the supplied optical

Connect a separately sold cable to

digital audio cable to input audio

ANALOG OPTICAL COAXIAL

Bluetooth.)

3. Adjust the volume.

2. Switch the input to TV.

Onkyo China Limited (Hong Kong)


http://www.hk.onkyo.com/

1301, 555 Tower, No.555 West NanJing Road, Jing'an District, Shanghai, China 200041,

http://www.cn.onkvo.com/

# **BASIC OPERATION**

# **Using Main Unit Controls**



Regarding the buttons on the main unit: The buttons on this unit are touch sensitive switches. Therefore, they may respond poorly depending on how they are pressed or not respond when pressed fast and consecutively.

## 1. ⊕ (ON/STANDBY) button/INPUT button

- To turn the standby: Press and hold for 3 seconds. The indicators go off.
- **To input the source:** Press once to switch. Switches in the order of TV  $\rightarrow$  USB  $\rightarrow$ Bluetooth each time the button is pressed.
- Auto Power On function: The unit automatically turns on when audio signal 6. Left channel speaker is output from the TV. To switch on/off this function, press and hold first (
- and then  $\bigcirc$  + for about 3 seconds. When this function is set to on, the indicator flashes once. It flashes twice when this function is set to off.
- Auto Standby function: The unit automatically enters the standby mode if the status with no operation and sound continues 5 minutes. To switch on/off this function goes off during standby. press and hold first 📵, and then 📦 🛑 for about 3 seconds. When this function is set to on, the 🖵 indicator flashes once. It flashes twice when this function is set to of 8. Right channel speake

## 2. INPUT source indicators

Switches the power on/standby, Also, switches the input source.

• To turn the power on: Press once when this unit is turned off.

- Lights when the source is TV.
- Lights when the source is USB.
- Lights when the source is Bluetooth.

## 3. + VOLUME -/+ buttons

Allows to adjust the volume by 1 step in the 0 to 30 range. • Pressing the - + buttons together will mute audio. The status indicator on the

Switches the sound mode of input sound as desired. The mode switches in th order of MUSIC  $\rightarrow$  NEWS  $\rightarrow$  MOVIE  $\rightarrow$  MUSIC  $\rightarrow$  each time the button is pressed. You can select the mode for each input source (TV, USB and Bluetooth).

- MUSIC Mode: Gives concert hall-like sound effect.
- **NEWS Mode:** Allows to comfortably listen news programs.
- MOVIE Mode: Creates powerful 3D sound effect suitable for enjoying movie

## 5. SOUND MODE indicators


Lights according to the selected sound mode

- MUSIC Lights in the music mode. NEWS Lights in the news mode.
- MOVIE Lights in the movie mode
  - Lights when the input signal is Dolby Digital.

Lights white when the power is on. It keeps flashing during mute. It flashes just once every time volume is adjusted or the input or sound mode is changed. It

# **Using Remote Controller**

## **How to Use Remote Controller**



## How to Replace Remote Controller Battery



3. INPUT buttons

Switches the input source.

press the 🔫 button.

page 16 for connecting

5. SUBWOOFER +/- button

6. SOUND MODE button

7. USB operation buttons

temporarily stops the audio.

listening to the sound. The default setting is 0

• MUSIC Mode: Gives concert hall-like sound effect

Allows operation when the input source is USB.

• **NEWS Mode:** Allows to comfortably listen news programs.

Allows to adjust the volume by 1 step in the 0 to 30 range.

Switches the sound mode of input sound as desired. The mode switches in the

order of MUSIC  $\rightarrow$  NEWS  $\rightarrow$  MOVIE  $\rightarrow$  MUSIC  $\rightarrow$  each time the button is pressed

• **MOVIE Mode:** Creates powerful 3D sound effect suitable for enjoying movies.

• button: Pressing once returns the audio to the beginning of the file being

played. Pressing twice continuously returns it to the previous file. Then the

audio will skip back to the previous file each time the button is pressed.

• 🕪 button: Pressing during stop starts playback. Pressing during playback

• (>>) button: The audio skips to the next file each time the button is pressed.

You can select the mode for each input source (TV, USB and Bluetooth).

4. VOLUME +/- buttons

SOUND MODE

H44 ) (►/II) (►► )

ONKYO

RC-877S

Turns the audio off temporarily. Press again to cancel muting.

Muting will also be canceled when the volume is changed or the power is

The Status indicator flashes when the audio is muted.

1. (b) (ON/STANDBY) button

Switches the power on/standby.

2. ☒ (Mute) button

turned off and or

- **To play the TV sound:** Turns the TV on and press the button.
- To play music from a USB flash drive: Connect the USB flash drive and
- To play music from a Bluetooth device: Press the (1) button. Refer to

- Allows to adjust the subwoofer level by 1 step in the -10 to +10 range while

Steps 3 and 4 need to be performe

on the Bluetooth device.

# . On the Bluetooth device, select

- the unit (Onkyo LS-T10) to make a connection. other remote controller cannot be operated.
- For details on operation, see the instruction manual of the Bluetooth device.
- If the operation does not start as normal within the 33 feet (10 m) range, get the Bluetooth device clos • Learning function: You can operate the unit with a TV remote controller by assigning
- If a passcode (password, passkey c
- When the pairing is completed, the indicator lights.
- 4. Start playback

1. Turn the unit on.

the pairing starts.

• The pairing will end in about 30 seconds

and the indicator starts flashing slowly


2. Press 🔞

- If you reset Bluetooth of this unit or removed the registration of this unit from the Bluetooth device, perform pairing (see above) again. VOLUME +
- unit to start pairing.

Playing via Bluetooth Connection

Within 33 ft (10m)

# **Using TV Remote Controller**



- It is recommended to select buttons that do not prevent TV operation when assigning remote controller. In such case, you can synchronize the mute status of the unit and the the functions to your remote controller. TV by pressing and holding the Mute button on your TV remote controller. Signal of some types of remote controller may not be received by the unit. In that case To disable the preprogrammed function, press and hold first ⊕, and then - for about
- 10 seconds. When the preprogrammed function is successfully disabled, 🖵 indicator flashes 3 times, then any TV remote controller cannot be used to operate the unit. When you want to re-enable the preprogrammed function, perform the same operation. When • The (a) indicator flashes faster, and the preprogrammed function is successfully re-enabled,  $\square$  indicator flashes once, then you can use any remote controller using preprogrammed function.

To control the preprogrammed functions: Varieties of TV remote controllers have been

## reprogrammed on this unit, which may lead to unintended operation from the other remote introller than your TV remote controller. In such case, press and hold first $|\Theta|$ and then |-|, and then ress either volume or mute button on your TV remote controller 2 or 3 times to turn on the controlling function. When the controlling function is set to on, the 🔲 indicator flashes twice, and then, the

- Controlling function may not be set to some TV remote controllers.
- To cancel the controlling function, press and hold first 🗐 and then 🗐 for about 10 seconds. When the controlling function is successfully cancelled, 🖵 indicator flashes once, then you can use any remote controller using preprogrammed function.
- to the unit and retry the operatio he functions to the buttons of the remote controller. Perform the following buttor operation, when the 📮 indicator starts flashing, direct your TV remote controller to remote PIN code) is requested, enter "0000 control sensor of this unit and press the button to assign on the TV remote controller 3 times.
  - When the Learning function is successfully set,  $\square$  indicator flashes twice. \* Press ( button first when pressing and holding the buttons together.

## plug it in again. $|\langle (\bullet) \rangle| \rightarrow | \odot |$ The unit turns off unexpectedly

Learning function Button operation (Press simultaneously for 3 seconds)

## • To connect any other Bluetooth device, press and hold the button of the main $[(\bullet)] \rightarrow [-]$ VOLUME -

## The unit will automatically enter standby mode when Auto Standby launches.

plugged into the wall outlet.  $(\rightarrow P.8)$ 

Unplug the power cord from the wal

outlet, wait 10 seconds or more, then

Can't turn on the unit

use the remote controller supplied with the unit

**Troubleshooting** 

Theck the items below if you have any problem

Before requesting repair: If the unit does not work or accept control, try resetting the unit to it

⊕ - + (\*\*)

1. Press and hold the |⊕| button on the main unit and the |−| |+| buttons for 10 seconds.

When reset is complete, the three INPUT source indicators flash and the unit automatically enters the

factory defaults and check if your problem is solved. Perform the following reset procedure.

## the power, it turns off again • The protection circuit has been Make sure that the power cord is properly activated. Remove the power cord from

Button operation (Press simultaneously for 3 seconds)

 $(\bullet)$   $\rightarrow$  + + -

 $\boxed{ ( \bullet ) ) } \rightarrow \boxed{ \oplus } + \boxed{ + }$ 

 $(\bullet)$   $\rightarrow$   $\bigcirc$  +  $\bigcirc$ 

he wall outlet immediately. Make sure hat all cables and input sources are properly connected, and leave the unit with its power cord disconnected for 1 hour. After that, reconnect the power cord and turn the power on. If the unit turns off again, unplug the power cord

and contact your Onkyo dealer.

The unit turns off and after restoring

# Noise can be heard

he unit, unplug the power cord from t Do not bind the power cord, connection all outlet immediately and contact your cables and other audio cables with a band.

noke, smell or abnormal noise is produced

There's no sound, or it's very quiet

are pushed in all the way.  $(\rightarrow P.7, 8)$ 

Make sure that the input of device is

connected properly.  $(\rightarrow P.7, 8)$ 

When the Status indicator flashes i

The base sound cannot be heard

The protection circuit in the subwoofe

temperature. Disconnect the power

cord from the outlet and reconnect after

may have tripped due to a rise in

white, the muting is enabled. Pre

Make sure that all audio connecting plugs

- An audio cable may be picking up interference. Try repositioning your
- Make sure that there is no obstacle or reflection between the unit and the

## The remote controller doesn't work

- Make sure that the battery is installed
- or Volume -/+ on the remote controller or the Volume +/- buttor simultaneously on the unit to disable the muting.  $(\rightarrow P.14)$
- Make sure that none of the connecting cables are bent, twisted, or damaged
  - to direct sunshine or invertertype fluorescent lights. Relocate if necessary.

control sensor. (→P.13)

# Playing USB Memory

The unit supports USB memory formatted using FAT12, FAT16 and FAT32 file system. • The unit is compatible with MP3

sampling rate of 16, 22.05 or 24 kHz

MPEG2.5 Audio Layer3 format with a

sampling rate of 8, 11.025 or 12 kHz

and 8 to 160 kbps bit rate

and 8 to 64 kbps bit rate

this unit.

You can play MP3 files stored on the

root folder only. MP3 files stored on

the other folders cannot be played on

- playback and following audio format is supported. - MPEG1 Audio Layer3 format with a
- sampling rate of 32, 44.1 or 48 kHz and 32 to 320 kbps bit rate MPEG2 Audio Layer3 format with a

- with the correct polarity.  $(\rightarrow P.13)$
- Make sure that the remote controlle is not too far away from the unit, and that there's no obstruction between the remote controller and the unit's remote
- The unit supports USB flash drives only. Make sure that the unit is not subjected Note, however, that playback may not be possible with some USB flash drives.

The unit contains a microcomputer for signal processing and control functions. In very rare situations, severe interference, noise from an external source, or static electricity may cause it to lockup. In the unlike event that this happens, unplug the power cord from the wall outlet, wait

at the material will be recorded

nkyo is not responsible for damages

ch as CD rental fees) due to

insuccessful recordings caused by

e unit's malfunction. Before you

ord important data, make sure

at least five seconds, and then plug it back in.

> If it doesn't work properly, please try resetting (→P.18).